

Hobbywing 30A Quickrun WP-16BL30 Brushless Car ESC



HWQRWP16BL30

Rating: Not Rated Yet

Price

Sales price R599,00

[Ask a question about this product](#)

Manufacturer [Hobbywing](#)

Description

Best for 1:18 and 1:16 scale cars
External programming port is easily connected to the LED Program Card (purchase separately) when setting the ESC.
Proportional brake with 8 steps of maximum brake force adjustment and 8 steps of drag brake force adjustment.
8 steps of acceleration (launch) adjustment from "soft" to "Very aggressive" to fit different kinds of models, tires and tracks.
Multiple protections: Low voltage cut-off protection / Over-heating protection / Throttle signal loss protection / Motor lock-up protection.
One-button (the "SET" button on the ESC) sets the ESC. All parameters easily reset to factory default settings.
Compatible with optional Digital LED Program Card.
SPECS
Cont. Peak Current: 30A
30A/180A/0.002s
Motor Type Supported: Senseless Brushless Motor
Car Applicable: 1:18 and 1:16 On-road/Off-road/Buggy/Monster
With Input: 2S LiPo or 3 cell NiMH
1. On-road: 2435 brushless or smaller motor with the KV smaller than 800
2. Off-road/Buggy/Monster: 2435 brushless or smaller motor with the KV smaller than 6000
With Input: 3S LiPo or 3 cell NiMH
1. On-road: 2435 brushless or smaller motor with the KV smaller than 5500
2. Off-road/Buggy/Monster: 2435 brushless or smaller motor with the KV smaller than 3000
ESC Output: 6V/1A (Linear Mode)
Size: Weight: 30(L) x 25(W) x 16(H) / 28g

External Program Port: Not Available
No cooling fan

Reviews

There are yet no reviews for this product.